Camelion®

3-in-1 LED Rechargeable Light Kit



Model No.: RT81 **Instruction Manual** PLEASE READ THIS MANUAL BEFORE YOU USE THE PRODUCT, AND SAVE IT FOR REFERENCE.

(L) CAUTIONS

GB

- Do not expose to fire.
- Do not use this product in high temperatures.
 Keep this product in a dry place while charging.
- Keep this product away from water and other liquids.
 This product should be recharged immediately when the light
- starts to dim. Disconnect the product from its charging port once fully charged.
 Close the cover on the input port properly.
- If the rechargeable light is not used on a regular basis, recharge this product once every six months to preserve battery life.
 Do not look directly into the light. This can damage your eyes. This is not a toy. This product should be used only under adult

Main Features

- 3 interchangeable heads for different lighting needs
 5 Lighting Modes High / Medium / Low / SOS / Strobe
 Super Bright 600 Im (flashlight head), 400 Im (work light head), 200 Im (flexible gooseneck head)
- Work light turns around in 360 degrees horizontally and vertically
 Concealed USB port with LED charging indicator
- · A carrying case included for storing components

Package Includes

- $3 \times \text{Light Heads}$ $1 \times 18650 \text{ Battery}$
 - 1 × USB Cable
- 1 × Swivel Hook & Holder 1 × Storage Carrying Case 1 × Shoulder Strap 1 × Instruction Manual

Product Details

Flashlight head with adjustable focus – This head is used to light up chosen spots. To adjust the light beam, slide the head forward and backwards.



Worklight head - This head provides powerful light from a COB LED panel. The dual axis pivot design enables the head



Flexible gooseneck head with adjustable focus - In this configuration, the user can light up difficult-to-reach areas with the use of a compact and versatile light head. Light beam can be adjusted by sliding the head forward and backward.



— 3 —

Power base – The power base is used to energize the 3 different LED light heads. The base has a powerful integrated magnetic base allowing users to work hands free.



Charging Indicator


Specifications

Component Picture	
Component Name	Power Base
Power Source	3.7V, 2600mAh 18650 Li-ion battery
Charging Time	3.5 h
Dimensions	ø 33 × 141 mm / ø 1.3 x 5.55 in
Weight	170 g / 0.37 lb
Ingress Protection	IP54

Component Picture	
Component Name	Flashlight Head
Light Source	Lumileds Luxeon HL2X
Lighting Modes	High / Medium / Low / SOS / Strobe
Lumen Output	High: 600 lm / Medium: 300 lm / Low: 150 lm
Continuous Operating Time	High: 3 h / Medium: 6 h / Low: 12 h
Beam Distance	250 m / 820.21 ft
Dimensions	ø 35 × 70 mm / ø 1.38 x 2.76 in
Weight	68 g / 0.15 lb
Ingress Protection	IP54

— 5 —


反面



Component Picture	
Component Name	Flexible Gooseneck Head
Light Source	Osram P8
Lighting Modes	High / Medium / Low / SOS / Strobe
Lumen Output	High: 200 lm / Medium: 100 lm / Low: 50 lm
Continuous Operating Time	High: 6.5 h / Medium: 11.5 h / Low: 26 h
Beam Distance	100 m / 328.08 ft
Dimensions	ø 31.5 x 432 mm / ø 1.24 x 17 in
Weight	103 g / 0.23 lb
Ingress Protection	IP54

— 6 —

Lighting Modes




How to Use

1 USING the Light

1) Insert the rechargeable battery provided in the packaging into the power base. The negative pole of the battery should be facing outward.




2) Select the light head to be used and insert it into the power base until it clips firmly.



- 3) Short press the button switch on the power base to turn on the light. WITHIN 4s, short press again to toggle the modes from High>Medium>Low>Strobe>SOS>OFF. AFTER 4S, short press again will turn off the light under any lighting mode.
- 4) For hands-free operation, attach the magnetic base to a metal surface or use the hook to hang it somewhere.

2 Changing the Light Head

Pull the red lock ring towards the handle while pulling the light



-7-

3 Charging the Light

Otestore	Power I	ndicator	Charging Indicator			
Status	green	red	green	red		
Sufficient Battery Power	√					
Low Battery Power		√				
Charging in Progress				√		
Fully Charged			√			

- Remove the input port cover located on the power base. Connect the input port to a certified USB output source with the included
- USB charging cable. 2) The charging indicator turns on and stay red during charging.
 3) The indicator will turn green when fully charged.
- After fully charged, disconnect the light and remove the cable, close the cover on the input port properly.

— 9 —

Camelion One (1) Year Limited Warranty

Camelion warrants that this product (the "Product") will be free from defects in Camelion warrants that this product (the "Product") will be free from defects in material and workmanship for a period of one (1) year from the date of purchase (the "Warranty Period"). For defects reported during the Warranty Period, Camelion will, at its discretion, and subject to Camelion's product support analysis, either repair or replace defective Product. Replacement parts and products will be new or serviceably used, comparable in function and performance to the original part and warranted for the remainder of the original Warranty Period. CAMELION'S LUABILITY HEREUNDER IS EXPRESSLY UMITED TO REPLACE MENT OR REPAIR OF THE PRODUCT. TO THE MAXIMUM EXTENT PERMITTED BY LAW, CAMELION SHALL NOT BE LUABLE TO ANY PURCHASER OF THE PRODUCT OR ANY THIRD PARTY YER ANY SPECIAL. INDIFFECT CONSCOURNITAL OR EXEMPLARY PARTY FOR ANY SPECIAL, INDIRECT, CONSEQUENTIAL OR EXEMPLARY DAMAGES, INCLUDING BUT NOT LIMITED TO, LOST PROFITS, PROPERTY DAMAGE OR PERSONAL INJURY RELATED IN ANY WAY TO THE PRODUCT HOWSOEVER CAUSED, EVEN IF CAMELION HAD KNOWLEDGE OF THE HOWSOEVER CAUSED, EVEN IF CAMELION HAD KNOWLEDGE OF THE POSSIBILITY OF SUCH DAMAGES. THE WARRANTIES SET FORTH HEREIN ARE IN LIEU OF ALL OTHER WARRANTIES, EXPRESS, IMPLED, STATUTORY OR OTHERWISE, INCLUDING, WITHOUT LIMITATION, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE, AND THOSE ARISING FROM COURSE OF DEALING, USAGE OR TRADE PRACTICE. IN THE EVENT THAT ANY APPLICABLE LAWS IMPOSE WARRANTIES, CONDITIONS OR OBLIGATIONS THAT CANNOT BE EXCLUDED OR MODIFIED, THIS PARAGRAPH SHALL APPLY TO THE GREATEST EXTENT ALL OWER DRY SICH LAWS

This Limited Warranty is made solely for the benefit of the original purchaser of the This Limited Warranty is made solely for the benefit of the original purchaser of the Product from Camelion or its approved reseller or distributor and is not assignable or transferable. To make a warranty claim, the purchaser must: (1) request and obtain a return merchandise authorization ('RIMA') number and return location information (the 'Return Location') from Camelion Support by emailing support(@-camelionhattery.com; and (2) send the Product, including RIMA number and receipt to the Return Location provided. DO NOT SEND IN PRODUCT WITHOUT FIRST OBTAINING AN RIMA FROM CAMELION SUPPORT. THE ORIGINAL IN IDEMLASED IS DESPONSIBLE (AND IN USE DREPMAN ALL I ORIGINAL PURCHASER IS RESPONSIBLE (AND MUST PREPAY) ALL PACKAGING AND TRANSPORTATION COSTS TO SHIP PRODUCTS FOR WARRANTY SERVICE, NOTWITHSTANDING THE ABOVE, THIS LIMITED WARRANTY IS VOID AND DOES NOT APPLY TO PRODUCTS THAT:

— 10 —

SHALL APPLY TO THE GREATEST EXTENT ALLOWED BY SUCH LAWS.

(a) were misused, mishandled, subjected to abuse or careless handling, accident, improperly stored, or operated under conditions of extreme voltage, temperature, shock, or vibration beyond Camelion's recommendations for safe and effective use; (b) improperly installed, operated or maintained; (c) are/were modified without the persess written consent of Camelion; (d) have been disassembled, altered or repaire by anyone other than Camelion; (e) had defects which were reported after the Warranty Period. THIS LIMITED WARRANTY DOES NOT COVER! (1) normal wear and tear; (2) cosmetic damage that does not affect functionality, or (3) Products where the Camelion serial and/or lot number is missing, altered, or defaced.

For any questions regarding your warranty or product contact Camelion Support at: Email: support@camelionbattery.com

or write to: Camelion Battery Co., Ltd. 705, Cyber Times Tower A, Tian'an Cyber Park, Shenzhen, China 518041 MADE IN CHINA



RECYCLING
This product bears it and electronic equip must be handled pu TELINU
This product bears the selective sorting symbol for Waste electrical and electronic equipment (WEEE). This means that this product must be handled pursuant to European directive 2012/19/EU in order to be recycled or dismantled to minimize its impact on the environment.

environment.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation. Please not let hat changes or modifications of this product is not expressly approved by the Please not that changes or modifications of this product is not expressly approved by the NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference by radio or television reception, which can the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.

- Increase the separation between the equipment and receiver.

- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.

- Consult the dealer or an experienced radio/TV technician for help.





RT81-GBA1

工艺要求

尺寸: 210*200mm 材质:80克书纸 颜色: 单黑

折页形式:按参考线

图纸编码		设计 蒋策 日期		期	202	3.6.16	
图纸名称	说明书	审核	李才强	日	期		
产品型号	RT81	批准	王道兵	日	期		
品牌	Camelion	THIRD ANGLE			单	位	MM
订单号				1	比	例	1:1
	※ 制市 水 循由 池 右 阻 小 ヨ			Ī	├—		

主要修改内容

升级充电接口,修改图和参数

版本 修改日期

A1 2023.6.16

Camelion. 深圳市飞狮电池有限公司 Camelion Battery Co., Ltd. 页码 1/x 该文档版权为camelion公司所有,未经本公司许可,不得随意更改,不得转发给第三方