

USB Fast Charger McPower, 65W

1x USB-C PowerDelivery, 1x USB-A QuickCharge

TECHNICAL DETAILS: Input: 100-240V AC · Maximum output power: 65W · USB-C output with Power Delivery: 5V max. 3.0A / 9V max. 3.0A / 12V max. 3.0A / 15V max. 3.0A / 20V max. 3.25A · USB-A output with Quick Charge: 5V max. 3.0A / 9V max. 3.0A / 12V max. 2.5A / 20V max. 1.5A · Output when used simultaneously: · USB-C1 + USB-C2: 45W + 20W (max. 65W) · USB-C1 + USB-A: 45W + 18W (max. 63W) · USB-C2 + USB-A: 7.5W + 7.5W (max. 15W) · USB-C1 + USB-C2 + USB-A: 45W + 7.5W + 7.5W (max. 60W)

Protection: Overcurrent, overvoltage and short-circuit protection

Efficiency specifications of the USB ports: · USB standby consumption: less than 0.1 W · No-load power consumption according to Regulation (EU) No. 2019/1782: · Average efficiency: approx. 84,40%

SAFETY INSTRUCTIONS: Please read all safety instructions carefully and keep them for future reference. This USB power adapter is intended solely for charging and operating compatible devices via the integrated USB-A and USB-C ports. Use the product only as described in this manual. The power adapter may only be connected to an AC power supply that matches the values stated on the rating label. Incorrect input voltage or frequency may cause damage to the device or lead to hazardous situations. Ensure that the power adapter is adequately ventilated during operation and is not covered or used near heat sources. Operate the device only in dry indoor environments and avoid any contact with water or other liquids, as this may result in electric shock, short circuits, or fire hazards. Use only suitable and high-quality USB cables. Always insert the connectors carefully and never pull the cables out forcefully to prevent damage. When using the USB-C port, especially with devices that support Power Delivery, be aware that higher voltages and currents may be supplied. Therefore, use only proper, certified cables and ensure that the connected devices are compatible with the respective power level. If the device is used with both USB-A and USB-C simultaneously, the maximum total output power of the power adapter must not be exceeded. The power adapter must not be opened, modified, or repaired. Damage, unusual deformation, discoloration, or excessive heat may indicate a defect. In such cases, immediately disconnect the product from operation and do not continue to use it.



DISPOSAL INSTRUCTIONS: By separating, recycling and disposing of old appliances in this way, you are making an important contribution to protecting our environment. Packaging can be disposed of free of charge in accordance with local regulations at the appropriate collection centres. According to the European WEEE Directive, electrical and electronic appliances may not be disposed of with household waste. Their components must be recycled or disposed of separately, as toxic and hazardous components can cause lasting damage to health and the environment if disposed of improperly. As a consumer, you are obliged under the German Electrical and Electronic Equipment Act (ElektroG) to return electrical and electronic equipment free of charge at the end of its life to the manufacturer, the point of sale or to public collection centres set up for this purpose. Details are regulated by the respective state law. The wheeled bin symbol on the product, operating instructions and/or packaging indicates these regulations.



DE: Eine mehrsprachige Version dieser Anleitung und die Konformitätserklärung finden Sie unter folgendem Link:

EN: A multilingual version of this manual and the Declaration of Conformity can be found at the following link:

FR: Vous trouverez une version multilingue de ce manuel et la déclaration de conformité sur le lien suivant:

ES: Encontrará una versión multilingüe de estas instrucciones y de la declaración de conformidad en el siguiente enlace:

<http://ettgroup.de/product/1300670>